








KAREL

KAREL MS224 KAREL MS128 KAREL MS48S KAREL MS38S

PRIVATE AUTOMATIC BRANCH EXCHANGES















QUICK REFERENCE CARD

- Line Access  _____
- Intercom _____
Extension number. _____
- Marked Call  **7 9 0** + External number. _____
- Call Transfer / Inquiry  +Extension number, hang up. To retrieve the call . _____
- Last Number Redial _____
While receiving busy tone on the line, **# 6 0** _____
- Selective Line Access  **7** +Line number. (For example: **7 0 1** to access line 01) _____
- Call Pick-Up  **8 2** + Ringing extension number. _____
- Call Back _____
While receiving busy tone **8 1** To cancel: **8 1** _____
- Follow Me _____
8 5 + Extension number. To cancel: **8 5**, hang up _____
- Follow Me No Answer _____
8 6 + Extension number. To cancel: **8 6**, hang up _____
- Do Not Disturb _____
8 3 1 To cancel: **8 3 0** _____
- Signalling Busy Extension _____
While receiving busy tone, **1**, wait. _____
- Intrusion _____
While receiving busy tone, **0**. To retrieve call on hold 

 : Subject To Authority

 : Hook Flash

FOR MORE INFORMATION REFER TO USER'S GUIDE

- Calling From Common Pool  **5** + (**0 0 - 9 9**) Common pool register number.
- Private Pool Entry _____  **8 4** + (**1 - 9**) Private pool register number, external number, hang up.
- Calling From Private Pool _____  **6** + (**1 - 9**) Private pool register number. _____
- Password Definition _____  **8 3 6** + **X X X** (000-250 3 digit password). _____
- Phone Lock _____  **8 3 7** + Password + **1** To unlock: **8 3 7** + Password + **0** _____
- Doorphone Call _____  **1 0** (For capacities higher than 6/18 **1 1 0**) _____
- Reminder _____  **8 3 8 7** + Reminder hour (00-23) minute (00-59). _____
- Pager _____
To Activate: **7 4 1** To Cancel: **7 4 0** _____
- Last Number Auto-Dial _____  **7 7 0**; From private pool **7 7** + (**1 - 9**) private pool register number
- Paging _____  **8 6 7** + Extension number. General paging **8 6 6** _____
(to handsfree phones) Group paging: **8 6 5** + Extension number of any member of the group. _____
- Call Park _____  **4** (for LT phones and operator **3**). To retrieve: **4** _____
- Conference _____
To include an extension:  **5**, extension number, . During a line to include a line:  **4** (for operator **3**) call the external party,  **9** _____

 : Subject To Authority

 : Hook Flash

FOR MORE INFORMATION REFER TO USER'S GUIDE

REV AAB - ING